

## Putting a call on hold

1. Press key, caller is put on hold.
2. To retrieve the call press key.

## Speed dial

1. Configure speed dial on web page (Number keys 0-9).
2. Long press the corresponding number key to achieve speed dial.

## Phonebook

1. Add speed dial contacts on webpage.

## Regulatory Compliance

### Federal Communication Commission (FCC) — USA

This device complies with Part 15 of FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received; including interference that may cause undesired operation.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in residential installation. This equipment generates, uses, and can radiate radio frequency energy, and if it is not installed and used in accordance with the instruction manual, it may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

**Warning:** Any changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment complies with Part 68 of the FCC rules and the requirements adopted by the ACTA. On the bottom of this equipment is a label that contains, among other information, a product identifier in the format US: 311IPNANH2UV2. If requested, this number must be provided to the telephone company.

Fanvil Technology Co., Ltd  
Website: [www.fanvil.com](http://www.fanvil.com)  
Email: [sales@fanvil.com](mailto:sales@fanvil.com) [support@fanvil.com](mailto:support@fanvil.com)  
Tel: +86-755-2640-2199 Fax: +86-755-2640-2618  
Add: 10/F Block A, Dualshine Global Science Innovation Center, Honglang North 2nd Road, Bao'an District, Shenzhen, China

# Fanvil

## V1.0


## Packaging list




Handset



Base



Quick Installation Guide



Handset Cord

## Keys features



Hold key, Hold/Resume the call



Hands-free key  
Activate/deactivate hands free



Mute key, with red color LED  
In idle mode: ringer off  
In communication mode:  
mute/un-mute a call



Volume +/- key  
In idle mode or during ringing:  
increase or  
decrease ringer volume  
In communication: increase or  
decrease earpiece, headset or  
hands-free volume



Message waiting indicator,  
with two-color LED



Redial key, Access to  
redial the last record




DSS Key, It can be set as  
function key/speed dial  
key, etc.

## Installation the device

Please follow the instructions in below picture to install the device.

### • Wall mounting (without screws and screw anchors)

- ① Drill two holes in the wall, the vertical distance between the two holes is 136.2 or 161.2mm;
- ② Drive in 2 screw anchors and screws in turn;  
**Note:** 5mm is reserved between the screw cap and the wall for easy installation of the phone base.
- ③ Connect the Ethernet cord, handset cord and power;
- ④ Align the wall mounting holes on the base with the screws made in step 2, slide down to complete the installation.



## H2U-V2

## Quick Installation Guide





Fanvil Technology Co., Ltd  
[www.fanvil.com](http://www.fanvil.com)

P/N:CJBA100315A0

### • Connecting to the Device

Please connect power adapter, network, and handset to the corresponding ports as described in below picture.

- ① Power port: connect the power adapter.
- ② Network port: connecting local area network or internet.
- ③ Handset port: connect IP Phone handset.



Handset

## Configuration

### Configuration via Web

1. Get the IP: Long press key, the IP Phone will report the IP address by itself.
2. Login: Input the IP address in the web browser. The PC and phone should be in the same IP address segment (The default username and password are both 'admin' .)
3. Configure: Select network/account etc, and fill the relevant content.
4. Save the configuration.

## Making a call

1. **Direct dialing:** lift the handset and enter the phone number, press key .
2. **Hands-free:** enter phone number press key and press or vice versa.

## Accepting a call

1. **Using the handset:** pick up the handset.
2. **Using the handsfree:** pick up the handset, and press .

## Redial

1. Press key, redial a call number.

## Call Mute

1. Press to Mute the microphone during the call.
2. Press again to un-mute the conversation.